

# MAGNETIC CONTACTS

• Hermetically Sealed Switches • Rhodium Over Gold Reeds • UL Listed • High Grade Magnets • Multiple Colours

	MODEL No.	CONTACT	DIMENSIONS	GAP	SPECIAL FEATURES
CONTACT	PS-1523		<ul style="list-style-type: none"> <li>Switch: 50.8 x 14.3 x 12.7mm</li> <li>Magnet: 50.8 x 14.3 x 12.7mm</li> </ul>	W-I-D-E-R GAP <b>15.9mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>Concealed mounting screws and terminals</li> <li>Durable magnet</li> <li>Maximum contact rating:</li> </ul>
	PS-1541		<ul style="list-style-type: none"> <li>Switch: 38.1 x 9.5 x 7.1mm</li> <li>Magnet: 38.1 x 9.5 x 7.1mm</li> </ul>	W-I-D-E-R GAP <b>12.7mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>610mm wire leads</li> <li>Durable magnet</li> <li>Maximum contact rating: 130VDC, 0.5A, 10W</li> </ul>
	DC-1551*		<ul style="list-style-type: none"> <li>Switch: 34.1 x 13.5 x 6.4mm</li> <li>Magnet: 34.1 x 13.5 x 6.4mm</li> </ul>	W-I-D-E-R GAP <b>22.2mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>457mm wire leads</li> <li>Durable magnet</li> <li>With mounting screws and adhesive tape</li> <li>Maximum contact rating:</li> </ul>
	DC-1561*		<ul style="list-style-type: none"> <li>Switch: 27.8 x 12.7 x 6.4mm</li> <li>Magnet: 27.8 x 12.7 x 6.4mm</li> </ul>	W-I-D-E-R GAP <b>25.4mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>457mm wire leads</li> <li>Durable magnet</li> <li>With mounting screws and adhesive tape</li> <li>Maximum contact rating:</li> </ul>
	DC-1581		<ul style="list-style-type: none"> <li>Switch: 25.4 x 6.4 x 4.8mm</li> <li>Magnet: 25.4 x 6.4 x 4.8mm</li> </ul>	W-I-D-E-R GAP <b>7.9mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>Simple installation/457mm wire leads</li> <li>Durable magnet</li> <li>With mounting nails and adhesive tape</li> <li>Maximum contact rating:</li> </ul>
	DC-2531		<ul style="list-style-type: none"> <li>Switch: 50.8 x 9.5 x 6.4mm</li> <li>Magnet: 50.8 x 9.5 x 6.4mm</li> </ul>	W-I-D-E-R GAP <b>19.0mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Slim design</li> <li>Durable magnet</li> <li>With mounting screws, adhesive tape and terminal screw cover-up tape</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
	DC-2541		<ul style="list-style-type: none"> <li>Switch: 63.5 x 19.0 x 15.9mm</li> <li>Magnet: 63.5 x 19.0 x 15.9mm</li> </ul>	W-I-D-E-R GAP <b>22.2mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Industry standard model</li> <li>Also for heavy steel doors</li> <li>With mounting screws, cover and spacer</li> <li>Maximum contact rating:</li> </ul>
MICROMINI	DC-1571	The World's Smallest 	<ul style="list-style-type: none"> <li>Switch: 16.7 x 7.1 x 1.6mm</li> <li>Magnet: 16.7 x 7.1 x 1.6mm</li> </ul>	W-I-D-E-R GAP <b>7.9mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>279mm wire leads</li> <li>Durable magnet</li> <li>With mounting nails</li> <li>Maximum contact rating: 28VDC, 0.1A, 3W</li> </ul>
OVERHEAD DOOR	PS-2023		<ul style="list-style-type: none"> <li>Switch: 107.2 x 38.1 x 9.5mm</li> <li>Magnet: 107.2 x 15.9 x 15.9mm</li> </ul>	W-I-D-E-R GAP <b>76.2mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>Adjustable L bracket</li> <li>699mm armoured cable</li> <li>Durable magnet</li> <li>Maximum contact rating: 200VDC, 0.5A, 10W</li> </ul>
RECESSED	PS-1711		<ul style="list-style-type: none"> <li>Switch: 44.5 x 12.7mm dia</li> <li>Head: 34.9mm flange</li> </ul>	<b>Rollerball</b>	<ul style="list-style-type: none"> <li>C/C loop – 12.7mm diameter</li> <li>For concealed mount</li> <li>610mm wire leads</li> <li>With mounting screws and spacer</li> <li>Maximum contact rating: 130VDC, 0.5A, 10W</li> </ul>

**THE ALEPH W-I-D-E-R GAP GUARANTEE:** Aleph rates all contacts on the "Make" (closed circuit) gap. The actual "Break" (open circuit) gap is always 50% greater than the "Make" gap we list! **RESULTS:** False Alarm



**ALEPH EUROPE**  
The First Name In Detection

	MODEL No.	CONTACT	DIMENSIONS	GAP	SPECIAL FEATURES
RECESSED	DC-1611		<ul style="list-style-type: none"> <li>Switch: 25.4 x 6.4mm dia.</li> <li>Magnet: 20.6 x 6.4mm dia.</li> </ul>	W-I-D-E-R GAP <b>19.0mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>6.4mm diameter/457mm wire leads</li> <li>Durable magnet</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
	DC-1631		<ul style="list-style-type: none"> <li>Switch: 14.3 x 6.4mm dia.</li> <li>Magnet: 14.3 x 6.4mm dia.</li> </ul>	W-I-D-E-R GAP <b>9.5mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Mini size</li> <li>457mm wire leads/6.4mm diameter</li> <li>Durable magnet/Simple installation</li> <li>Maximum contact rating: 28VDC, 0.01A, 0.3W</li> </ul>
	DC-1811*		<ul style="list-style-type: none"> <li>Switch: 31.8 x 25.4mm dia.</li> <li>Magnet: 31.8 x 25.4mm dia.</li> </ul>	W-I-D-E-R GAP <b>34.9mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>For heavy steel doors</li> <li>Self locking/Rugged and rigid</li> <li>25.4mm diameter/457mm wire leads</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
PRESS FIT	DC-1621*		<ul style="list-style-type: none"> <li>Switch: 31.8 x 9.5mm dia.</li> <li>Magnet: 31.8 x 9.5mm dia.</li> </ul>	W-I-D-E-R GAP <b>19.0mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/9.5mm diameter</li> <li>Crush resistant/457mm wire leads</li> <li>Durable magnet/Simple installation</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
	PS-1650		<ul style="list-style-type: none"> <li>Switch: 31.8 x 9.5mm dia.</li> <li>Magnet: 19.0 x 9.5mm dia.</li> </ul>	W-I-D-E-R GAP <b>12.7mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop</li> <li>Stubby switch/Long magnet</li> <li>Simple installation/457mm wire leads</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
	DC-1651*		<ul style="list-style-type: none"> <li>Switch: 19.0 x 9.5mm dia.</li> <li>Magnet: 19.0 x 9.5mm dia.</li> </ul>	W-I-D-E-R GAP <b>11.1mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Stubby switch and magnet</li> <li>For tight fit windows and thin doors</li> <li>Crush resistant/Durable magnet</li> <li>Simple installation/457mm wire leads</li> <li>Maximum contact rating: 28VDC, 0.5A, 10W</li> </ul>
3T-EOL	DC-3531		<ul style="list-style-type: none"> <li>Switch: 50.8 x 7.1 x 9.5mm</li> <li>Magnet: 50.8 x 7.1 x 9.5mm</li> </ul>	W-I-D-E-R GAP <b>19.0mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Slim surface mount</li> <li>Third terminal for EOL resistor connection</li> <li>Gold plated screws and terminals for corrosion resistance</li> <li>With mounting screws and terminal cover-up tape</li> </ul>
	DC-3541		<ul style="list-style-type: none"> <li>Switch: 63.5 x 19.0 x 15.9mm</li> <li>Magnet: 63.5 x 19.0 x 15.9mm</li> </ul>	W-I-D-E-R GAP <b>22.2mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Standard surface mount</li> <li>Third terminal for EOL resistor connection</li> <li>Gold-plated screws and terminals for corrosion resistance</li> <li>With mounting screws, cover and spacer</li> </ul>
	DC-3621		<ul style="list-style-type: none"> <li>Switch: 27.8 x 9.5mm dia.</li> <li>Magnet: 16.7 x 9.5mm dia.</li> </ul>	W-I-D-E-R GAP <b>12.7mm</b> Make	<ul style="list-style-type: none"> <li>C/C loop/Press fit</li> <li>Third terminal for EOL resistor connection</li> <li>Crush resistant</li> <li>Gold-plated screws and terminals for corrosion resistance</li> <li>Maximum contact rating:</li> </ul>
	DC-3711		<ul style="list-style-type: none"> <li>Switch: 50.8 x 19.0mm dia.</li> <li>Head: 31.8mm flange</li> </ul>	W-I-D-E-R GAP <b>Rollerball</b>	<ul style="list-style-type: none"> <li>C/C loop/Roller ball</li> <li>Third terminal for EOL resistor connection</li> <li>Gold-plated screws and terminals for corrosion resistance</li> <li>With mounting screws and spacer</li> <li>Maximum contact rating:</li> </ul>

\* Available with tamper. All available in white, grey and brown.