



detectomat

Push Button Detector

PL 3300 MCP-kit

order number : 32065



Intelligent push button detector for loop 3000 with bidirectional isolator, labeled symbol "Burning House":

- loop 3000 is a highly functional detection-system
- automatic addressing (soft-addressing)
- manual addressing (Easy Check)
- output for alarm at the detector

technical data

remarks	The detector zone(s) the MCP-Kit has been programmed in, need to be programmed as an MCP zone (conventional) via dpt 3000. The I-Check software identifies the kit as an AMD 3311.
operation voltage	15 up to 30 V loop powered
quiescent current	370 μ A
alarm current	5 mA
operation temperature	-10 °C up to +55 °C
humidity	max. 95 % non-condensing
protection class	IP 24 D
colour housing	red, RAL 3000
material	ABS
DIN-EN	54-11
dimensions	(H x W x D): 88 mm x 88 mm x 54 mm
catalogue page	52
weight	0 kg

errors and alterations excepted