

# The Ideal Solution for Entry/Exit Access Control

AY-L23 is a long-range wireless receiver that can activate electronic barriers, garage doors, home security systems, or any other device that can accept an auxiliary input. The receiver works with Rosslare's SA-23 wireless remote control transmitter. It can receive the remote control signal from up to 50 meters (164 ft) and can output the ID in two different Wiegand formats.



## MAIN FEATURES

- Excellent RF performance
- Modern, slender design
- Contains an internal antenna
- Includes optical wall and case tamper protection, including a tamper output signal
- Two different multi-Wiegand output formats
- SA-23-B2 remote control has two different ID outputs
- SA-23-B4 has four different ID outputs controlling Wiegand1 output of AY-L23
- Ultra-low current consumption
- Single control wire selects the LED color (green or orange)
- Mountable on a flat surface
- Receiver interfaces to any control panel with an available reader input
- Internal buzzer sounds when the unit successfully reads an RF signal



AY-L23 is compatible with Rosslare's door control systems, Rosslare's single/double/multi-door controllers:



**AC-215**  
2-Door  
Controller

\* UL Listed



**AC-215IP**  
2-Door  
Controller



**AC-225/IP**  
2-Door  
Controller

\* UL Listed



**AC-425/IP**  
4-Door  
Controller



• EN ISO 13485



**ROSSLARE**  
SECURITY PRODUCTS

www.rosslaresecurity.com

info@rosslaresecurity.com